

Transconductance (uMho) per vertical division

Volts / Step

	0.05	0.10	0.20	0.50	1.00	2.00	5.00
Vertical Current per Div							
50 uA	1,000	500	250	100	50	25	10
100 uA	2,000	1,000	500	200	100	50	20
200 uA	4,000	2,000	1,000	400	200	100	40
500 uA	10,000	5,000	2,500	1,000	500	250	100
1 mA	20,000	10,000	5,000	2,000	1,000	500	200
2 mA	40,000	20,000	10,000	4,000	2,000	1,000	400
5 mA	100,000	50,000	25,000	10,000	5,000	2,500	1,000
10 mA	200,000	100,000	50,000	20,000	10,000	5,000	2,000
20 mA	400,000	200,000	100,000	40,000	20,000	10,000	4,000
50 mA	1,000,000	500,000	250,000	100,000	50,000	25,000	10,000
100 mA	2,000,000	1,000,000	500,000	200,000	100,000	50,000	20,000

Beta per vertical division

Current/Step

	1 uA	2 uA	5 uA	10 uA	20 uA	50 uA	100 uA	200 uA	500 uA	1 mA	2 mA	5 mA	10 mA
Vertical Current per Div													
10 uA	10	5	2	1	1	0	0	0	0	0	0	0	0
20 uA	20	10	4	2	1	0	0	0	0	0	0	0	0
50 uA	50	25	10	5	3	1	1	0	0	0	0	0	0
100 uA	100	50	20	10	5	2	1	1	0	0	0	0	0
200 uA	200	100	40	20	10	4	2	1	0	0	0	0	0
500 uA	500	250	100	50	25	10	5	3	1	1	0	0	0
1 mA	1,000	500	200	100	50	20	10	5	2	1	1	0	0
2 mA	2,000	1,000	400	200	100	40	20	10	4	2	1	0	0
5 mA	5,000	2,500	1,000	500	250	100	50	25	10	5	3	1	1
10 mA	10,000	5,000	2,000	1,000	500	200	100	50	20	10	5	2	1
20 mA	20,000	10,000	4,000	2,000	1,000	400	200	100	40	20	10	4	2
50 mA	50,000	25,000	10,000	5,000	2,500	1,000	500	250	100	50	25	10	5
100 mA	100,000	50,000	20,000	10,000	5,000	2,000	1,000	500	200	100	50	20	10
200 mA	200,000	100,000	40,000	20,000	10,000	4,000	2,000	1,000	400	200	100	40	20
500 mA	500,000	250,000	100,000	50,000	25,000	10,000	5,000	2,500	1,000	500	250	100	50
1 A	1,000,000	500,000	200,000	100,000	50,000	20,000	10,000	5,000	2,000	1,000	500	200	100
2 A	2,000,000	1,000,000	400,000	200,000	100,000	40,000	20,000	10,000	4,000	2,000	1,000	400	200